

“STEEL STRING”

CLEAN DRIVE

MKII

PRODUCT MANUAL

LEVEL

Adjusts the output of the pedal.

GAIN

Adjusts the amount of saturation of the signal from boost below 12:00 to overdrive (from 1:00 and beyond).

JAZZ/ROCK

Jazz setting fattens and adds low-end; Rock increases highs and cuts low-end.


FILTER

Accentuates different mid-frequencies, acting as a pseudo tone knob.




The Steel String Clean Drive MKII faithfully recreates the tonality and feel of the iconic Dumble Steel String Singer amplifier in a stompbox format. Designed alongside a real Steel String Singer (#001), this 100% analog tone tool will do it all from Overdrive, to Fat Boost, to Compression, to EQ shaping and more. We took everything great about the original Steel String Clean Drive and put in a smaller enclosure. The MkII also features a Jazz/Rock switch, giving you more control over bass and high-frequency response. Get the unmistakable Crystal-Clear Overdrive and Fat Clean Tones from albums like "Texas Flood", "Venus Isle", and "Continuum" through any clean amp platform.


SUGGESTED SETTINGS




“Gravity”




“B.B. Ray Shepherd”




“EJ”



“Little Lowell”



“Browne Sound”



“Always On”

SPECIFICATIONS

Controls	Volume, Tone, Gain, Rock/Jazz
Connections	Input, Output, 9VDC
Dimensions	4.29" x 2.25" x 1.68"
Power Connector	2.1mm barrel (center negative)
Input Impedance	2.2M ohms
DC Voltage	8.0-9.6V[*9.8V MAX]
Current Consumption	Less than 10mA
Output Impedance	100k ohms

VERTEX™

www.verticeffects.com